



# APC1000

## Inverter Phase Checker

**IP52** Water & Dust resistant

**NC** Non-contact detection

**Apo** Auto power off

**PS** Phase sequence detection



Model	APC1000
Function/Application	Phase detection, live wire examination, power inspection, phase loss judgment, breakpoints finding, breakpoints positioning.
Measurement Method	Non-contact detection
Voltage Range	Three-phase voltage, 70-1000V AC (45Hz ~ 66Hz)
Operating Frequency	50 Hz / 60 Hz (±10%)
Test Method	Non-contact clamping
Altitude	< 2000 m
Battery	2 * 1.5V AA alkaline batteries Continuous working time: more than 20 hours
Remark	The frequency range of other variable-frequency power supply is not examined
Packing	Carton: 5pcs

# AVD24

## Non-Contact AC Voltage Detector



**PO** Auto power off

**LED** LED indication

**B** Buzzer

**HL** High/Low voltage mode

**V** AC voltage detection

**NC** Non-contact

Model	AVD24
AC Voltage (Low)	24 V-1000 V
AC Voltage (High)	90 V-1000 V
Frequency Range	50 / 60 Hz
Buzzer	✓
LED Indication	✓
Battery	2 * 1.5V AA alkaline batteries
Packing	Carton: 40 pcs